

3300 WATTS

GP SERIES

Portable Inverter Generator

GENERAC[®]



GP3300i Portable Inverter Generator featuring PowerRush™ Advanced Technology

GP3300i

PORTABLE INVERTER GENERATOR

Light and quiet power on the go.

Power whenever and wherever you need it, the Generac GP3300i inverter featuring new, advanced PowerRush™ technology delivers over 50 percent more starting capacity for your RV essentials and other motor-driven equipment—so you can do more with less.* Quiet inverter power—perfect for outdoor activities in a compact and lightweight solution.

OVER 50% MORE STARTING CAPACITY

with new, advanced PowerRush™ technology so you can do more with less*

QUIET INVERTER POWER

that reduces sound emissions and provides optimal performance



EASY-TO-CARRY

with a compact and lightweight built-in handle

ONE SIMPLE-TO-USE DIAL

that integrates start/run/stop functions with PowerDial™



POWERRUSH™

DOUBLE YOUR POWER

PARALLEL KIT (#7668-0)

A Generac parallel kit allows you to double your power when pairing two inverter generators together with the same output.† Parallel kit sold separately.



*Increases electrical current upon demand; above rated output when starting electric motors.

†Connect any two Generac 3000 or 3500 Series' inverters for twice the power. Applies when pairing two inverter generators with the same output. Parallel kit sold separately.

CONTROL PANEL FEATURES



GENERATOR STATUS LIGHTS

Ready, overload and low oil

ECONOMY MODE

Provides excellent fuel economy and noise reduction

USB OUTLETS

Charge mobile devices including smartphones and tablets

PARALLEL READY

Connect two inverters together for twice the power (parallel kit sold separately)

HOW MUCH POWER DO YOU NEED?

Sizing a portable generator is easy. Check out this example:

- 1** CHOOSE WHICH DEVICES YOU WANT TO POWER AT THE SAME TIME.
- 2** RECORD THE RUNNING WATTS LISTED FOR EACH DEVICE. IF YOUR DEVICE ONLY LISTS AMPS, MULTIPLY THE AMPS BY 120V TO GET WATTAGE. EX. 15A X 120V = 1800 WATTS
- 3** ADD THE RUNNING WATTS TOGETHER FOR ALL DEVICES. THIS IS THE MINIMUM RUNNING WATTAGE REQUIREMENT FOR YOUR NEEDS.

DEVICE	RUNNING WATTS	GENERATOR SIZE
RV Air Conditioner (13,500 BTU) [†]	1250	Minimum running Watts for your needs ↓ 2300 RUNNING WATTS
LED/LCD Television	120	
Blue Ray Player	15	
Slow Cooker	250	
Cell Phone Charger	10	
RV Microwave	600	
Total	2245	

[†]Motor load, demands higher Watts at start-up.
 Watts listed are approximate. Check your appliance for actual requirements. Total wattage requirements assumes intermittent starting of devices.

	DEVICE	RUNNING WATTS
RECREATION	RV Air Conditioner (13,500 BTU) [†]	1250
	Cell Phone Charger	10
	Box Fan - 20"	100
	Tablet	20
	Blue Ray Player	15
	LED/LCD Television	120
	Slow Cooker	250
	Laptop Computer	75
	Coffee Maker	900
	RV Microwave	600
JOB SITE	Blender	1000
	Hair Dryer	1500
	Lithium Ion Battery Charger	360
	Air Compressor [†]	1000
	Circular Saw [†]	1400
	Hand Drill [†]	600
	Belt Sander [†]	1200
	Reciprocating Saw [†]	1440
	Table Saw [†]	1800
	Airless Paint Sprayer	1080
HOUSEHOLD	Wet Dry Vac	900
	Quartz Halogen Work Light	1000
	Refrigerator/Freezer [†]	700
	Lights	600
	Desktop Computer	400
	Sump Pump [†]	2100
	Toaster	1200
	Window AC (12,000 BTU) [†]	3250

GP3300i

PORTABLE INVERTER GENERATOR



SPECIFICATIONS

SERIES	GP3300i
Model #	7154
Configuration	50ST/CSA
Running Watts	2500
Starting Watts	3300
Engine Type	Generac OHV
Engine Displacement	149cc
Starting Method	Recoil Pull Start
Low Oil Shutdown	Yes
Fuel Tank Capacity (Gallons)	1.06
Run Time @ 50% Load	4.5 hours
Run Time @ 25% Load	7 hours
Rated Voltage	120V
Low Total Harmonic Distortion (THD)	Less than 3%
Outlets	(2) 120V 20A 5-20R Duplex, (1) 120V 30A L5-30R Twist Lock, (2) USB Outlets
Parallel Ready	Yes
Handle Style	Single, Molded Into Enclosure
Dimensions (L" x W" x H")	22.3 X 13.4 X 18.4
Product Weight	59.5 lbs
Warranty - Residential	3 Year Limited
Warranty - Commercial	1 Year Limited

All portable specifications and models subject to change. Please consult factory for availability.

PARALLEL KIT

Model # (Configuration)	7668-0
Receptacle Type	(1) 120V 50A 14-50R, (1) 120V 30A TT-30R (RV)
Covered Outlets	Yes
Rated 120 VAC Amperage	50 Amp
AC Rated Voltage	120 V
Warranty - Residential	90 Day Limited
Warranty - Commercial	90 Day Limited
Dimensions (L x W x H)	9.84" x 4.33" x 8.27"

GENERAC®