


The **EG4000CL** Economy Generator From Honda



4000 watts of rugged, reliable, and economical portable power. Honda DAVR (Digital Auto Voltage Regulator) maintains voltage stability within $\pm 1\%$ of 60Hz during operation. **New CO-MINDER™ advanced carbon monoxide detection system** continuously measures CO levels and automatically shuts down the generator before detected CO levels near the generator become dangerously high.*

FEATURE

- **4000 watts** (33.3A/16.6A) 120/240V
- **Honda-exclusive DAVR** (Digital Auto Voltage Regulation)
- **Fuel Efficient**, runs up to 14.8 hours at 1/2 load on 6.3 gallons of fuel
- **CO-MINDER™** automatically shuts down the generator if it detects carbon monoxide gas reaching unsafe levels
- 125V **GFCI** Outlet Protection
- **Honda GX270 commercial engine**
- **Low 66 dB(A) sound level** @ 1/2 load
- **120/240V selector switch**
- Optional **2-wheel kit with handles**
- Protected by **Oil Alert®**
- **Honda 3-Year Residential Warranty/ Honda 3-Year Commercial Warranty†**



SPECIFICATIONS

EG4000CL

Engine	Honda GX270
Displacement	270cc
Max AC Output	4000w max. 120/240V (33.3/16.7A)
Rated AC Output	3600w rated (30/15A)
Receptacles	20A 125V GFCI Duplex (2) 30A 125V Locking Plug 20A 125/250V Locking Plug
Voltage Regulation	DAVR
Starting System	Recoil
Fuel Tank Capacity	6.3 gal
Run Time Per Tankful	10.1 hours at rated load 14.8 hours at 1/2 load
Noise Level**	67 dB(A) at rated load 66 dB(A) at 1/2 load
Dimensions (L x W x H)	26.8" x 20.9" x 22.5"
Dry Weight	147 lbs.
USDA Spark Arrestor	Standard
CO-MINDER™	Standard



Find out more at gen.honda.com.

*This product complies with the ANSI/PGMA G300-2018 standard. †Warranty applies to all Honda GX Series Engines and GX Series-powered Honda Power Equipment, 100cc or larger, purchased or put into rental service since January 1, 2010. Exceptions apply. See full warranty details at honda.com. Does not apply to EU1000 models. **Tested in accordance with ISO 9614-2, sound pressure level calculated at 23 Feet (7 meters) using the front plane of the generator (control panel side) per ASHRAE Handbook 2017. Please read the owner's manual before operating your Honda Power Equipment and never use in a closed or partly enclosed area where you could be exposed to odorless, poisonous carbon monoxide. Connection of a generator to house power requires a transfer device to avoid possible injury to power company personnel. Consult a qualified electrician. © 2020 American Honda Motor Co., Inc. C1026