

INDUSTRIAL

| SPECIFICATIONS | | EB3000cKAG | EB4000X | EB5000X | EB6500X | | | |
|--|--|---|---|---|---|------------|-----------------------|--------|
| Engine | | Honda GX200 | Honda iGX270 | Honda iGX390 | Honda iGX390 | | | |
| | | Single cylinder, overhead valve, air-cooled | Single cylinder, overhead valve, air-cooled | Single cylinder, overhead valve, air-cooled | Single cylinder, overhead valve, air-cooled | | | |
| Displacement | | 196cc | 270cc | 389cc | 389cc | | | |
| AC output | | 120V 3000W max. (25.0A) 2600W rated (21.7A) | 120/240V 4000W max. (33.3/16.7A) 3500W rated (29.2/14.6A) | 120/240V 5000W max. (41.7/20.8A) 4500W rated (37.5/18.8A) | 120/240V 6500W max. (54.1/27.1A) 5500W rated (45.8/22.9A) | | | |
| iAVR AC output | | N/A | 5000W (41.7/20.8A) for 10 sec. | 7000W (58.3/29.2A) for 10 sec. | 7000W (58.3/29.2A) for 10 sec. | | | |
| Receptacles | | D, F | C(2), F, G | C(2), F, H | C(2), F, H | | | |
| DC output | | 12V, 144W (12A) | N/A | N/A | N/A | | | |
| Starting system | | Recoil | Recoil | Recoil | Recoil | | | |
| Fuel tank capacity | | 2.7 gal. | 6.2 gal. | 6.2 gal. | 6.2 gal. | | | |
| Run time per tankful | | 6 hrs. @ rated load, 9.39 hrs. @ 1/2 load | 10.1 hrs. @ rated load, 16.0 hrs. @ 1/2 load | 8.1 hrs. @ rated load, 11.2 hrs. @ 1/2 load | 6.9 hrs. @ rated load, 10.4 hrs. @ 1/2 load | | | |
| Dimensions (L x W x H) | | 17.3" x 15.7" x 18.9" | 41.9" x 27.2" x 29.2" | 41.9" x 27.2" x 29.2" | 41.9" x 27.2" x 29.2" | | | |
| Noise level | | 68 dB @ rated load 97 LwA†† | 71 dB @ rated load 97 LwA†† | 72 dB @ rated load 99 LwA†† | 73 dB @ rated load 100 LwA†† | | | |
| Dry weight | | 68.4 lbs. | 185 lbs. | 214 lbs. | 220 lbs. | | | |
| FEATURES | | EB3000cKAG | EB4000X | EB5000X | EB6500X | | | |
| Honda OHV engine | | • | • | • | • | | | |
| Electric start/Remote start option | | | | | | | | |
| Oil Alert® | | • | • | • | • | | | |
| Auto Throttle® | | | • | • | • | | | |
| Eco-Throttle™ (load dependent operation) | | | | | | | | |
| Electronic ignition | | • | • | • | • | | | |
| Simultaneous AC/DC use | | • | | | | | | |
| Circuit breakers | | • | • | • | • | | | |
| Fuel gauge | | • | • | • | • | | | |
| i-Monitor | | | | | | | | |
| Wheel kit standard | | | • | • | • | | | |
| iAVR | | | • | • | • | | | |
| DAVR | | | • | • | • | | | |
| CycloConverter™ | | • | | | | | | |
| Inverter | | | | | | | | |
| One switch for engine/fuel valve on/off | | | | | | | | |
| Full tubing frame for protection | | • | • | • | • | | | |
| USDA-qualified spark arrester/muffler | | • | • | • | • | | | |
| Fully enclosed for quieter operation | | | | | | | | |
| 120/240V selector switch | | | • | • | • | | | |
| GFCI/neutral bond | | GFCI ONLY | • | • | • | | | |
| Residential warranty | | 3 Years | 3 Years | 3 Years | 3 Years | | | |
| Commercial warranty | | 3 Years | 3 Years | 3 Years | 3 Years | | | |
| ††LwA is an international noise level measurement that uses a weighting factor to reflect noise "tonality" in addition to the sound power (dBA) level. | | Receptacle Key | RECEPTACLE | DESCRIPTION | PLUG # | RECEPTACLE | DESCRIPTION | PLUG # |
| | | | B | 15A 125V Duplex | 5-15P | D | 20A 125V GFCI Duplex | 5-20P |
| | | | C | 20A 125V Duplex | 5-15P or 5-20P | E | 20A 125V Locking Plug | L5-20P |