

INVERTER GENERATOR





POWERING YOUR life.

> Model 201120


UPC **817198025728**

∑★ Warranty 3 Years











ELECTRIC START

Push button start includes **BATTERY**



ULTRA OUIET

LOW NOISE - high performance



EZ START DIAL

Confusion free ENGINE START-UP




INTELLI [회장]되다

5-MODE display with power meter



PARALLEL READY

Link 2 units for DOUBLE POWER













Parallel



CARBON MONOXIDE AUTO-SHUTOFF SYSTEM









Q Specifications

START TYPE Electric, Recoil

VOLTAGE (V) AC 120

VOLTMETER Intelligauge w/ Power Meter

212 **ENGINE SIZE (cc)**

FUEL TYPE Gasoline or Propane

GASOLINE CAPACITY (gal.) 2.3

10W-30 **OIL TYPE** OIL CAPACITY (fl. oz./mL) 16.9/500

LOW OIL SHUT-OFF Yes

EMISSIONS EPA III/CARB Our 4650-watt inverter generator meets ANSI/PGMA G300-2018 requirements and features CO Shield, the Carbon Monoxide auto shutoff system. The 212cc engine runs for up to 14 hours on gasoline or up to 21 hours with a 20-lb propane tank plus you can increase your power with the optional Parallel Kit.

Inside the box

GENERATOR OPERATOR'S MANUAL OIL FUNNEL ENGINE OIL

PROPANE HOSE 6 FT. **USB ADAPTER** 8/10 MM WRENCH **SPARK PLUG SOCKET**

REVERSIBLE PHILLIPS/ FLATHEAD SCREW-DRIVER

GASOLINE OR PROPANE

What You Need

(!) *Specifications, descriptions and illustrations are subject to change without notice.



