10 kw

#### POWERPROTECT

Standby Generators

RESIDENTIAL STANDBY GENERATORS SPECIFICATIONS









# Sleek and compact — this standby generator packs a powerful punch.

Equipped with a unique front-facing exhaust for easy placement and installation, our 10kW¹ unit ensures all your home's essential appliances and power needs are covered during even the worst outages.

#### **FEATURES**



#### Warranty

6-Year limited warranty of parts, labor, and travel included for the entire term. The industry's most comprehensive warranty over time.<sup>2</sup>



#### **Compact Size**

50% smaller than competitive generators in its class<sup>3</sup> allows for a hassle-free installation.



#### **Assembled and Engineered in USA**

Briggs & Stratton generators are designed and assembled in the USA.<sup>4</sup>



#### **Commercial-Grade Vanguard® Engine**

Powerful engine built in the USA for commercial applications providing power for electronics.



#### **Flexible Placement Options**

Approved for installation as close as 18" to a building<sup>5</sup> with easy service access to the engine and alternator.



# Symphony® II Power Management System (optional)

Customizable to your home's needs offering prioritized whole house power with a more affordable standby generator.



#### **Schaeffer Full Synthetic Generator Oil**

Shields engine to reduce wear and tear and allows enhanced cold weather start-up protection to -20° F.



## POWERPROTECT.

## **Standby Generators**

#### RESIDENTIAL STANDBY GENERATORS SPECIFICATIONS



Generator Set Rating	
Model Name	PP10
Model Number	040684
Running Power (Liquid Propane/Natural Gas) kW <sup>1</sup>	10 / 8
Running Amperage (Liquid Propane/Natural Gas) Amps	41.7 / 33.3
Voltage	120 / 240
Circuit Breaker Amps	50


Engine	
Manufacturer	Vanguard®
Frequency Regulation Steady State	+/-2.5%


Sound Rating <sup>7</sup>	
Normal Operating Sound <sup>7</sup>	67 dBA

Fuel Consumption <sup>6</sup>	
No Load (BTU/hr)	NG - 60,000 / LP - 59,000
Half Load (BTU/hr)	NG - 111,000 / LP - 107,000
Full Load (BTU/hr)	NG - 169,000 / LP - 164,000

Available Accessories		
Battery Warmer	6182	
Maintenance Kit	6873	
Remote Status Monitor	6144	
Fuel Regulator Warmer	6845	

Product Dimensions		
Overall Dimensions (in / mm)	28 x 24.5 x 34.8 / 712 x 622 x 883	
Packaged Dimensions (in / mm)	39 x 33.5 x 42 / 991 x 851 x 1063	
Assembled Weight (lbs / kg)	272 / 123	
Packaged Weight (lbs / kg)	330 / 150	





- <sup>1</sup> This generator is rated in accordance with UL (Underwriters Laboratories) 2200 (stationary engine generator assemblies) and CSA (Canadian Standards Association) standard C22.2 No. 100-14 (motor and generators).
- $^{\rm 2}$  See operator's manual or BRIGGS and STRATTON.com for complete warranty details.
- <sup>3</sup> 50% smaller footprint than competitors
- <sup>4</sup> Of global and U.S. parts
- <sup>6</sup> The installation manual contains specific instructions related to generator placement in addition to NFPA 37, including the requirement that carbon monoxide detectors be installed and maintained in your home or business.
- <sup>6</sup> Fuel consumption rates are estimated based on normal operating conditions. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances fuel flow rates may vary depending on these factors.
- <sup>7</sup> Per ISO 3744. Sound level measurement at other locations around generator may differ depending on installation, based on lowest microphone at 7m. Normal operation based on average household usage.

 $Briggs \& Stratton \ has a policy of continuous product improvement \ and \ reserves \ the \ right \ to \ modify \ its specifications \ at \ any \ time \ and \ without \ prior \ notice.$ 

This standby generator is not for Prime Power applications.

Published February 2023. Please visit BRIGGSandSTRATTON.com for the latest information.