

The **EU1000i** Super Quiet Generator From Honda



1000 watts of super quiet, portable power for fans, TVs, lights, and small power tools and appliances. **New CO-MINDER™ advanced carbon monoxide detection system** continuously measures CO levels and automatically shuts down the generator before detected CO levels near the generator become dangerously high.*

FEATURES

- **1000 watts** (8.3 A) of Honda Inverter 120V AC Power
- **Super quiet**, only 42 to 50 dB(A)
- **Light weight (less than 29 lbs.)** makes transporting easy
- **Fuel efficient**, runs up to 6.8 hours on 0.6 gallons of fuel
- **CO-MINDER™** automatically shuts down the generator if it detects carbon monoxide gas reaching unsafe levels
- **Advanced inverter technology** provides reliable power to computers and other sensitive equipment
- **Parallel with another EU1000i for additional power**
- **Oil Alert®, Overload Alarm and Eco Throttle®**
- Protected by **Oil Alert®**
- **USDA-qualified spark arrestor/muffler**
- **Honda 2-Year Residential Warranty/ Honda 1-Year Commercial Warranty†**



SPECIFICATIONS

	EU1000i
Engine	Honda GXH50
Displacement	49.4cc
Max AC Output	1000w max. 120V (8.3A)
Rated AC Output	900w rated (7.5A)
Receptacles	15A 125V Duplex
Frequency Regulation	Inverter
Starting System	Recoil
Fuel Tank Capacity	.55 gal
Run Time Per Tankful	3.0 hours at rated load 6.8 hours at 1/4 load
Noise Level**	50 dB(A) at rated load 42 dB(A) at 1/4 load
Dimensions (L x W x H)	17.8" x 9.5" x 14.9"
Dry Weight	28.7 lbs.
USDA Spark Arrestor	Standard
CO-MINDER™	Standard

Find out more at gen.honda.com.

*This product complies with the ANSI/PGMA G300-2018 standard. †See full warranty details at honda.com. **Tested in accordance with ISO 9614-2, sound pressure level calculated at 23 Feet (7 meters) using the front plane of the generator (control panel side) per ASHRAE Handbook 2017. Please read the owner's manual before operating your Honda Power Equipment and never use in a closed or partly enclosed area where you could be exposed to odorless, poisonous carbon monoxide. Connection of a generator to house power requires a transfer device to avoid possible injury to power company personnel. Consult a qualified electrician. © 2020 American Honda Motor Co., Inc. C1023